# GEFRAN MELT PRESSURE TRANSMITTERS M7 SERIES PERFORMANCE LEVEL 'c'

Voltage output



The M7 Performance Level 'c' series of Gefran are pressure transmitters for using in high temperature environment.

The main characteristic of this series is the capability to read temperature of the media up to  $400^{\circ}$ C.

The constructive principle is based on the hydraulic trasmission of the pressure.

The fluid-filled system assures the temperature stability. The phisical measure is transformed in a electrical measure by means of the strain-gauge technology.

## MAIN FEATURES

- Pressure ranges from: 0-35 to 0-2000 bar / 0-500 to 0-30000 psi
- + Accuracy: <  $\pm 0.25\%$  FSO (H); <  $\pm 0.5\%$  FSO (M)
- Fluid-filled system for temperature stability
- Mercury filling volume: M70 (30mm<sup>3</sup>); M71, M72 (40mm<sup>3</sup>)
- 1/2-20UNF, M18x1.5 standard threads; other types available on request
- · Other diaphragms available on request
- Autozero function on board / external option
- Standard diaphragm is 15-5 PH stainless steel with GTP coating
- 17-7 PH corrugated diaphragm with GTP coating for ranges below 100 bar-1500 psi

#### GTP (advanced protection)

Coating with high resistance against corrosion, abrasion and high temperature

## AUTOZERO FUNCTION

All signal variations in the absence of pressure can be eliminated by using the Autozero function.

This function is activated by closing a magnetic contact located on the transmitter housing.

The procedure is permitted only with pressure at zero.

## **TECHNICAL SPECIFICATIONS**

| Accuracy (1)  | H <±0.25% FSO (1002000 bar)<br>M <±0.5% FSO (352000 bar)   |  |
|---|--|--|
| Resolution  | 16 bit   |  |
| Measurement range   | 035 to 02000bar<br>0500 to 030000psi   |  |
| Maximum overpressure (without degrading performances)   | 2 x FS<br>1.5 x FS above 1000bar/15000psi  |  |
| Measurement principle   | Extensimetric  |  |
| Power supply  | 1830Vdc  |  |
| Maximum current absorption  | 15mA<br>(30mA with relay optional)   |  |
| Output signal Full Scale (FSO)  | 10,5Vdc  |  |
| Zero balance<br>(tollerance ± 0.25% FSO)  | 0,5Vdc   |  |
| Response time (1090% FSO)   | 8ms  |  |
| Output noise (RMS 10-400Hz)   | < 0.025% FSO   |  |
| Calibration signal  | 80% FSO  |  |
| Power supply polarity reverse protection  | YES  |  |
| Compensed temperature range housing   | 0+85°C   |  |
| Operating temperature range housing   | -30+85°C   |  |
| Storage temperature range housing   | -40+125°C  |  |
| Thermal drift in compesated range:<br>Zero / Calibration / Sensibility  | < 0.02% FSO/°C   |  |
| Diaphragm maximum temperature   | 400°C / 750°F  |  |
| Zero drift due to change in process temperature (zero)  | < 0.02 bar/°C  |  |
| Standard material in contact with process medium  | Diaphragm:<br>• 15-5PH with GTP coating<br>• 17-7 PH corrugated diaphragm<br>with GTP coating for ranges<br><100bar (1500psi)<br>Stem: • 17-4 PH |  |
| Thermocouple (model M72)  | STD : type "J" (isolated junction)   |  |
| Protection degree<br>(6-pole female connect)  | IP65   |  |
| FSO=Full scale output: (1) <code>BFSL</code> method (Best Fit Straight Line): includes combined effects of Non-Linearity, Hysteresis and Repeatability. |  |  |

## **MECHANICAL DIMENSIONS**



## SELF DIAGNOSTICS

Below the conditions detected by the sensor self-diagnostics:

- Cut cable / device non connected / broken power supply, output <0.25V</li>
- Pin detachment, output >11.125V
- Pressure above 200% of the span, output <11.125V
- Voltage monitor in case of overvoltage/undervoltage/ voltage variation in the electronics, output <0,25V
- Program sequence error, output < 0.25V
- $\cdot$  Overtemperature on the electronics, output <0.25V
- Error on the primary element output or on the first amplification stage, output <0.25V</li>

## OPTIONAL RELAY OUTPUT FOR EXCESS PRESSURE PROTECTION

Safety relay characteristics:

- $\cdot$  Activation threshold to be defined in the order code
- Rated carry current: 1A
- Rated voltage: 24Vdc ± 20%
- Switch accuracy: 2 x sensor accuracy
- Hysteresis: 2% FSO

| SUPPLY | OUTPUT           | RELAY<br>STATUS |
|--------|------------------|-----------------|
| OFF    | -                | OPEN            |
| ON     | < X%fs           | CLOSED          |
| ON     | > X%fs           | OPEN            |
| ON     | output < 0.25V   | OPEN            |
| ON     | output > 11.125V | OPEN            |

#### NAMUR COMPLIANCE



## AUTOZERO FUNCTION



The Autozero function is activated through a magnetic contact (external magnet supplied with the sensor).

See the manual for a complete Autozero function explanation.

#### **ELECTRICAL CONNECTIONS**



**Thermocouple for M72 model** Type "J" (153mm - 6" rigid rod)

Fixing pen clip

Autozero pen

TTER 601

**PKIT 379** 

**PKIT 378** 

#### ORDER CODE



GEFRAN reserves the right to make any kind of design or functional modification at any moment without prior notice



**GEFRAN** spa via Sebina, 74 25050 PROVAGLIO D'ISEO (BS) - ITALIA tel. 0309888.1 - fax. 0309839063 Internet: http://www.gefran.com